

### COMPONENTS - OTGGRSIN or OTGGRUSB

#### For use with:

- This product fits tables .25" - 2" thick.
- Fits all OTG standard grommets, except SL7130DS / SL6630DS / SL6030DS / SL4830DS
- Use a #6 x .5" wood screw (not included).
- Not recommended for surfaces less than .375". Take care to not pierce finished surfaces.

#### Specifications:

- 1-2- 15A, 120VAC tamper resistant receptacles
- 2.1A/10.5W USB charging ports
- 72" standard cord with NEMA 5-15 straight plug
- Recommended Table Thickness: 0.25" - 2"
- Recommended Table Cut Out: 60mm
- Fastening ring included secures unit to surface
- ETL listed for US and Canada

**STEP 1 - Determine the OTGGRSIN or OTGGRUSB mounting location (existing grommet hole).**

**STEP 2 - Remove Mounting Ring from OTGGRSIN or OTGGRUSB by unscrewing as shown in FIG 1. Retain for later use.**

**STEP 3 - Insert the OTGGRSIN or OTGGRUSB through the cutout from above and position as desired. Rotate Mounting Ring clockwise and tighten until OTGGRSIN or OTGGRUSB is secure in hole (FIG 2).**

**STEP 4 - Run the OTGGRSIN or OTGGRUSB power cord to a power outlet as needed.**

**STEP 5 - To ensure Mounting Ring doesn't turn loose, a screw should be inserted into Locking Hole to secure it to the underside of the worksurface. Take care not to pierce finished surfaces.**

**NOTE: A furniture Power Distribution Unit is not for permanent installation as part of the building structure and not for mounting in permanently-installed furnishings such as a fixed countertop.**

